

access

LIGHTING

Read & Save these Instructions Model: 62061/62062/62063 Installations & Operation Instructions

(1) TOOLS AND MATERIALS REQUIRED

- ❖ BLADE SCREW DRIVER
- ❖ ADJUSTABLE WRENCH
- ❖ WIRE CUTTERS
- ❖ WIRING SUPPLIES AS REQUIRED BY ELECTRICAL CODE

Attention:

Before assembling your lighting fixture, please read the following instructions. If you feel you do not have sufficient electrical experience, refer to a do-it-yourself wiring handbook or have your fixture installed by a qualified licensed electrician.

(2) GENERAL

1. To ensure the success of the installation, be sure to read these instructions and review the diagrams thoroughly before beginning.
2. All electrical connections must be in accordance with local codes, ordinances, or the National Electrical Code. If you are unfamiliar with methods of installing electrical wiring, secure the services of a qualified licensed electrician.
3. These fixtures are intended for mounting to a standard 4" x 2 1/4" deep metal octagon outlet box. The box must be directly supported by the building and U.L. Recognized.
4. Before commencing with the installation, **disconnect the power by turning off the circuit breaker** or by removing the fuse at the fuse box. Turning the power off using the light switch is not sufficient to prevent electrical shock or risk of fire.
5. Save these **IMPORTANT SAFETY INSTRUCTIONS** and refer to them when additions to or changes in the fixture configuration are made.
6. Do not install this fixture in hazardous locations.
7. Do not install any fixture assembly closer than 6 inches from any curtain or similar combustible material.

NOTE:

The important safeguards and instructions appearing in this manual are not meant to cover all possible conditions and situations that may occur. It must be understood that common sense, caution and care, are factors that cannot be built into any product. These factors must be supplied by the person(s) caring for and operating the fixture.

(3) UNPACKING THE FIXTURE

On checking the contents of the box you will find;

- ❖ Fixture assembly
- ❖ Glass panel
- ❖ 2" side pans
- ❖ Halogen bulb and tempered glass protectors
- ❖ Mounting hardware package

(4) PREPARE THE FIXTURE

Refer to figure 1 for illustration of fixture parts and assembly.

1. If you are replacing an existing fixture, disconnect and remove the old fixture. Expose the supply wiring from the junction box.
2. Feed the supply wires through the center hole in the mounting bracket (a) Secure the mounting bracket to the outlet box using 2pcs. Provided mounting screws (The fixed screws in the mounting bracket should be facing out from the wall).
3. **Wiring:**
 - Connect the **BLACK** supply wire to the **Black** wires of the fixture with supplied **wire connectors(b)**. Ensuring a secure connection.
 - Connect the **WHITE** supply wire to the **White** fixture wires and secure with the supplied wire connectors(b).
 - Attach the **ground (GREEN)** wire from the fixture to the box ground wire (or to the junction box ground terminal) and secure with the supplied wire connectors(b).
 - Secure all **wire connectors(b)**, connections with UL listed electrical tape (not supplied). Tuck wires carefully into junction box.
4. Insert the two protruding screws from the mounting bracket into the two holes allocated in the fixture back plate(c). Secure the fixture back plate to the wall with the supplied hex screws(d).
5. Insert Halogen bulb (e) between sockets located on the back a soft dry cloth. Fit the tempered glass protector (f) over the bulb assembly (**Do not touch the Halogen Bulb with Bare hands, use a soft dry cloth**)
6. Mount the side pan(k) to the back plate(c) with the supplied screws(l).
7. Attach the big glass panel(g) to the fixture housing(h) by fitting the protruding screws from the fixture housing through the holes allocated in the big glass panel. Secure with the supplied plastic grommet and knurled knobs(i).
8. Attach the fixture housing to the back plate(c) by aligning the holes on top of the fixture housing(h) with the holes on top of the back plate(c) secured with supplied screws(j).
9. Restore the electricity and check the operation of your new lighting fixture.

CAUTION:

- *Ensure that the Fitting is Cool and Switched off, Before Changing the Halogen Bulb.*
- *Do Not use Bulbs Exceeding Maximum Wattage, As Per Caution Label.*
- *Do Not use lamp without the supplied Tempered Protection Glass.*
- *Do Not Touch the Halogen Bulb or Protective glass while fixture is in operation.*
- *Do Not Operate the Lighting Fixture close to any Combustible Material.*

FIG (1)

